RESPIRONICS SIMPLYGO

PORTABLE OXYGEN CONCENTRATOR



#A0065



- Nonclinical style and ease of use make it appealing to residents
- Easy-to-remove battery for quick maintenance
- Multiple alarm types make troubleshooting easy

| Specifications: | |
|--------------------------|--|
| Flow Rate: | 0.5 - 2.0 continuous flow 1 - 6 lpm pulse in 0.5 lpm increments |
| O ₂ Purity %: | 87% - 96% |
| O ₂ Pressure: | 3 psi |
| Power Consumption: | 150W while charging 120W while not charging |
| Sound Level: | ≤ 43 dB at pulse setting 2 |
| Battery Life: | 3½ hours / 7 hours with extra battery |
| Dimensions: | 10"W x 6"D x 11½"H |
| Weight: | 10 lbs.; 11.5 lbs. with extra battery |
| Warranty: | 2 years |

Preventive Maintenance

Once Every 1 - 2 Years:



Check and, if necessary, change the inlet filter. We also recommend changing between residents.

When changing patients:



Discard oxygen tubing, cannula/mask, oxygen outlet connector, and humidifier bottle. Replace cabin filter. Clean concentrator cabinet. Inspect plugs, cords and components. Check oxygen concentration.