

AIRSEP FOCUS

PORTABLE OXYGEN CONCENTRATOR



#E1454

AIRSEP
A Chart Industries Company

Preventive Maintenance

Every 5,000 Hours:



Replace compressor felt filter.

Periodic Intervals:



Test the oxygen purity with each new resident and at periodic intervals determined by the equipment provider.

When changing patients:



Discard oxygen tubing, cannula/mask, oxygen outlet connector, and humidifier bottle. Replace cabin filter. Clean concentrator cabinet. Inspect plugs, cords and components. Check oxygen concentration.

- Lightest portable concentrator at less than 2 lbs.
- UltraSense technology is the most sensitive breath detection and delivery available
- Maximum portability and ambulation wearable with carrying bag, belt clip or shoulder strap
- Fully functional off battery, AC and DC

Specifications:

Flow Rate:	Pulse setting 2.0
Battery Life:	3.0 total hours (1½ hours per battery, two included)
O ₂ Purity %:	90% +5.5 / -3%
O ₂ Pressure:	Not published for pulse units
Power Consumption:	23.25W
Sound Level:	45 dBA
Dimensions:	6½"W x 2½"D x 4½"H
Weight:	1.75 lbs.
Warranty:	3 years unit; 1 year battery & accessories